

Magnetic Switch

Model No. LW904

Features

- Wireless window / door sensor
- Automatically switch LightwaveRF devices
- Switch lights / heating / power
- Does not require LightwaveRF Link
- Can be positioned anywhere
- Includes adhesive pads to adhere to frame
- Can also be attached to doors
- Battery powered (CR2032 coin cell)

Specification

RF frequency: 433 MHz

Batteries: 1 X CR2032 coin cell battery

Mounting: Adhesive pads included.

Operation: Can communicate directly with LightwaveRF Connect devices (not including heating)

Warranty: 2 year standard warranty

