

Smart Dimmer (1 Gang)

Model No. L21

Features

- 350W smart dimmer switch
- Control by smartphone (requires Link Plus)
- 2-way communication: check status
- Timers / schedule / triggers / scene lighting
- Voice control with HomeKit / Alexa / Google Home
- Standard wiring (no neutral required)
- Fits standard 35mm single back box
- 10mm spacer included
- Soft Start capability
- Colour customisable LED indicator
- Metallic finishes
- Auto calibrates to suit most dimmable LED lamps
- Can perform wire-free multiway switching

Specification

RF frequency: 868 MHz

Input rating: 220-240V~ 50Hz.

Output rating: 3W~350W max.

Incandescent Load: 20W-350W max (per gang)

LED load: see Lightwave compatibility charts

Back Box Depth: 35mm min

Spacer depth 10mm (7mm with recess)

Earthing: Not essential (double insulated)

Standby Energy Use: Less than 1W

Wiring: Neutral wire NOT required

Warranty: 2 year standard warranty

Environment: For indoor use only

Available Finishes

Stainless Steel

White Metal

Regulatory Standards

CE Marked

